



WHOLE HOME  
BACK-UP



OUTDOOR  
EVENTS



MARKET STALLS/  
MOBILE BUSINESS



AGRICULTURE  
& FARMING



Total harmonic distortion 6- 8%



## PRODUCT DETAILS

The Welling and Crossley P8750 is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is Euro 5 emissions compliant. The generously sized fuel tank and economical motor allows longer run times. The WC-P8750 packs a lot of power in a compact footprint.

## APPLICATIONS

- Work areas and construction sites to power lights, drills, saws, compressors, power tools etc.
- Whole home backup power
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls to power appliances

## FEATURES

- 2 x IP66 Outlets (single phase - 15 Amp)
- USB A and USB C outlets
- Recoil, Push-button electric, Wireless remote or 2 wire remote starting
- Steel frame with fold-out wheelbarrow style transport handle and large wheels
- 4-Stroke, air cooled, OHV engine
- Large 25L fuel tank
- Digital V/F/T Display (Volts, Frequency, Time)
- Low oil alarm, overload alarm, output indicator
- 2 year Welling and Crossley Warranty (battery excluded)

## TECHNICAL DATA

ALTERNATOR RATING	8.75kVa with AVR
POWER FACTOR	1.0
MAX. AC OUTPUT	7000W
RATED AC OUTPUT	6800W Max 15 amp
RATED MOTOR SPEED	3000rpm
RATED VOLTAGE	230/240V AC 1 Ph / 50Hz
ENGINE MODEL	WC420: Euro 5 emissions compliant
ENGINE TYPE	4 stroke, OHV, air cooled. Transistor ignition
DISPLACEMENT	420cc

OIL	1.1 litres SAE10W-30
SPARK PLUG	Torch F6TC, Champion RN9YC
DECIBELS @ 7M DISTANCE	99 dBA
FUEL TYPE	Petrol – 91 octane unleaded.
FUEL TANK CAPACITY	25L
FUEL CONSUMPTION	Approx 1.48 L/Hr @ 1/4 load
PACKAGING (L X W X H)	710 x 535 x 590mm
DIMENSIONS	L: 700mm W: 600mm H: 660mm
WEIGHT	90kg