



HOME ESSENTIAL
APPLIANCE BACK-UP



SMALL OUTDOOR
EVENTS



MARKET STALLS/
MOBILE BUSINESS



LIGHT
AGRICULTURE



Total harmonic distortion 6- 8%



EURO 5

PRODUCT DETAILS

The Welling and Crossley P3750 is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is Euro 5 emissions compliant. The generously sized fuel tank and economical motor allows longer run times. The WC-P3750 packs a lot of power in a compact footprint.

APPLICATIONS

- Work sites to power small to medium tools and lights
- Home backup power for essential appliances
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls for powering small appliances

FEATURES

- 2 x IP44 Outlets (single phase - 15 Amp)
- USB A and USB C outlets
- Recoil, Push-button electric, Wireless remote or 2 wire remote starting
- Steel frame with fold-out wheelbarrow style transport handle and large wheels
- 4-Stroke, air cooled, OHV engine
- Large 15L fuel tank
- Digital V/F/T Display (Volts, Frequency, Time)
- Low oil alarm, overload alarm, output indicator
- 2 year Welling and Crossley Warranty (battery excluded)

TECHNICAL DATA

ALTERNATOR RATING	3.75kVa with AVR
POWER FACTOR	1.0
MAX. AC OUTPUT	3200W
RATED AC OUTPUT	2800W Max 12 Amp
RATED MOTOR SPEED	3000rpm
RATED VOLTAGE	230/240V AC 1 Ph / 50Hz
ENGINE MODEL	WC230: Euro 5 emissions compliant
ENGINE TYPE	4 stroke, OHV, air cooled. Transistor ignition
DISPLACEMENT	223cc

OIL	0.6 litres SAE10W-30
SPARK PLUG	Torch F6TC, Champion RN9YC
DECIBELS @ 7M DISTANCE	97 dBA
FUEL TYPE	Petrol – 91 octane unleaded.
FUEL TANK CAPACITY	15L
FUEL CONSUMPTION	Approx 0.6 L/Hr @ 1/4 load
PACKAGING (L X W X H)	605 x 470 x 507mm
DIMENSIONS	L: 600mm W: 580mm H: 560mm
WEIGHT	45kg